LA-UR-02-2912

Title: | MEASURING RESIDUAL STRESS EFFECTS IN CT SPECIMENS

Author(s): | Michael B Prime, ESA-WR
Michael R. Hill, University of California, Davis
Hans-Jakob Schindler, MatTech, Winterthur, Swizterland

Los Alamos
NATIONAL LABORATORY

Measuring Residual Stress Effects in CT Specimens

Michael B. Prime

Los Alamos National Laboratory

Michael R. Hill

University of California, Davis

Hans-Jakob Schindler

MatTech, Winterthur, Swizterland

- Following the derivation in [1,2] The K_I from the release of *all* residual stresses up to a is given by:

$$K_{Irs}(a) = \frac{E'}{2B\dfrac{K_{IF}(a)}{F}}\frac{d(CMOD)}{da}$$

- A K_{IF} solution of sufficient accuracy is given in [3] as:

$$\frac{K_{IF}(a)}{F} = \frac{2.5934 - 3.625\tilde{a} + 32.5162\tilde{a}^2 - 76.1035\tilde{a}^3 + 117.416\tilde{a}^4 - 108.706\tilde{a}^5 + 54.3705\tilde{a}^6 - 11.4149\tilde{a}^7}{(1-\tilde{a})^{3/2}\sqrt{\pi\tilde{a}\tilde{W}}}$$

$$\tilde{a} = \frac{a + 0.25W}{1.25W}, \tilde{W} = 1.25W$$

- Measurement of height h works also: $\dfrac{dh}{da} \approx \dfrac{d(CMOD)}{da}$

- However using change in h before and after making slot can potentially even give the wrong sign for K_{Irs}

$$-\frac{d(CMOD)}{da} \Rightarrow -K_{Irs} \quad \text{correct}$$

$$+\Delta h \Rightarrow +K_{Irs} \quad \text{wrong}$$

Because of the equilibrium condition, this curve will always inflect at some point and give a change in the sign of the slope

1. M. B. Prime, "Measuring Residual Stress and the Resulting Stress Intensity Factor in Compact Tension Specimens," *Fatigue & Fracture of Engineering Materials & Structures*, **22**, 195-204, 1999.
2. H.-J. Schindler, W. Cheng, and I. Finnie, "Experimental Determination of Stress Intensity Factors Due to Residual Stresses," *Exp. Mech.* **37**, 272–277, 1997.
3. X. R. Wu and A. J. Carlsson, *Weight Functions and Stress Intensity Factor Solutions*, Pergamon Press, 1991.

Engineering Sciences & Applications Division

Los Alamos NATIONAL LABORATORY